

# Indian Institute of Science

E9-251: Signal Processing for Data Recording Channels

Instructor: Shayan G. Srinivasa

Home Work #1, Spring 2014

Late submission policy: Points scored = Correct points scored  $\times e^{-d}$ ,  $d = \#$  days late

**Assigned date:** Feb 3<sup>rd</sup> 2014

**Due date:** Feb 20<sup>th</sup> 2014.

---

PROBLEM 1: In this problem, you will build a simulator for the perpendicular recording channel. Assume that the transition response is  $h(t) = A \tanh\left(\frac{2t}{0.579\pi PW_{50}}\right)$ . In this case,  $PW_{50}$  is defined as the duration when the pulse  $h(t)$  changes from  $-\frac{A}{2}$  to  $+\frac{A}{2}$ . Define the channel bit density ( $cbd$ ) as  $\frac{PW_{50}}{T}$ .

- (1) Sketch  $h(t)$ , where,  $t$  is along the X-axis in nano-meter scale. Express  $h(t)$  in terms of the user bit density ( $ubd$ ) and code rate  $R$ . Study the effects of intersymbol-interference by varying  $ubd$  for a code rate  $R = 0.75$ .
- (2) The readback signal suffers from jitter noise associated with the fluctuations in the position  $t$  and the pulse width  $PW_{50}$  as well as electronic noise from read heads. Define the signal-to-noise ratio (SNR) for this technology appropriately. Evaluate the SNR in terms of  $ubd$ ,  $R$  and relevant noise statistics.
- (3) Generate non return to zero (NRZ) bits and obtain the read back response along with noise and interference for cases where  $ubd = \{1, 1.5, 2\}$ . Assume that the code rate is  $R = 0.75$ . What do you conclude?
- (4) Compute the time and statistical mean and autocorrelation for the read back signal. Is it ergodic in the mean and autocorrelation?
- (5) Sketch the schematic of the read back signal generation process. Include all the signal and noise paths up to a first order approximation.

(75 pts.)

NOTE: Your solution should include the original Matlab code along with necessary mathematical derivations followed by experiments, observations and conclusions.

PROBLEM 2: Refer to the paper by Evans et al. "Thermally induced error: Density limit for magnetic data storage," in Appl. Phys. Lett., 100, 102402, 2012. The authors introduce an additional factor called 'thermal writability' to assess areal density gains.

- (1) Sketch the areal density as a function of bit error rate (BER) during writing process for writing temperature  $T_{wr} = 730K$  and curie temperature  $T_c = 750K$ .
- (2) How do the areal densities in the previous part compare to the super paramagnetic limits?
- (3) If the error mechanism is assumed purely due to the writing process, what is the classical capacity of the recording channel? (Hint: You may approximate this with the binary symmetric channel). Translate the capacity numbers to areal densities.

(25 pts.)